

Get to Know Your Gear



CARRY IT

The handle on top of the EXTREME 350 makes it easy to carry, unlike other battery packs.

POWER IT

The EXTREME 350 is capable of charging any device; USB, 12V and AC outputs (requires inverter).

LEAVE IT

Leave the EXTREME 350 plugged in at home or in your cabin as a great emergency backup.

Getting Started

1. Be sure to **ACTIVATE YOUR WARRANTY** at www.GOALZERO.com/warranty
2. To use: plug your 12V car adapter (included) into the EXTREME 350 power pack.
3. Plug devices into the 12V car adapter. For more charging options use EXTREME UI (Universal Inverter) available at www.GOALZERO.com.

How to Use Your Gear

1 Charging Port

Use to charge EXTREME 350 from wall or solar panel.

2 12v output port

Attach EXTREME UI, use for chaining, or use to power 12V devices.



Comes With

12V car adapter

Technical Specs

Usage

Charges from the following:	Approx. charge time:
AC wall charger	6-7 hours
12V car charger	12 hours
BOULDER 30 solar panel	12-16 hours
Shelf Life	charge every 3-4 months
Chainable	yes, with other EXTREME 350s

Inputs

Charging port (8.0mm)	15-16V, 10A max (150W)
-----------------------	------------------------

Outputs

Chaining port (2x Powerpole)	11-13V, 30A max (400W), not regulated
*AC universal-port	400W, modified-sine wave user-switchable 110/220VAC
*USB port	5V, 0.5A (2.5W), buck regulated
*12V port (6.0mm, and car adapter)	11-14V, 10A max (120W), not regulated

Internal

Battery type	Lead-acid (AGM)
Battery capacity	350Wh (12V, 33Ah)
Battery voltage range	11-14.4V
Life-span	hundreds of cycles
Fuses	40A, 2x standard car fuses in parallel

General

Weight	25.7 lbs (11.7 kgs)
Dimensions	9x10x3 in (23x25.4x7.6 cm)
Warranty	12 months
Tested and Certified	FCC and CE
Operating useage temp.	32-104°F (0°-40°C)
Optimal storage temp.	70°F (21°C)

* Does not come with EXTREME 350 power pack. These outputs are included on the EXTREME UI, available at www.GOALZERO.com.

USER GUIDE



Frequently Asked Questions

What electronics will it power?

The EXTREME 350 is designed for larger electronic equipment, however heating devices (for example, space heaters) may draw too much power from the EXTREME 350 to be effective.

Is it weatherproof?

The EXTREME 350 will hold up in incimate weather, but it is not waterproof. Make sure the ports are dry before using the device.

How long can the battery hold a charge?

If left unused, the battery will hold a charge for 3 months. It is best to leave your EXTREME 350 plugged in to prolong the life of the battery.

Do I need an inverter?

To run any AC or USB device you will need an EXTREME UI (Universal Inverter) available at www.GOALZERO.com.

Compatible With

Most 12V devices, like:

Laptop
Fan
Cell phone
Smart phone
GPS
MP3 player

GOAL ZERO products:

GUIDE 10 PLUS battery pack
ROCK OUT speaker
BOLT flashlight
BLAZE headlamp
LIGHT-A-LIFE light
ESTELLA light

**For more input options, purchase the EXTREME UI at www.GOALZERO.com*

- Fill out your warranty
- Watch demo video
- Download this manual



CONTACT US:

Toll Free: 888.794.6250
14864 Pony Express Road
Bluffdale, UT, 84065

WWW.GOALZERO.COM

We proudly support Tifie Humanitarian
WWW.TIFIE.ORG